

Slim Duct



- Flexible Installation
- Easier Drain Pump Installation
- Slim Design
- Easy to Maintain



Pre Filter



Easy Filter



High Lift-Up



Smart Control



Wired RC

Model			NJ026LHXEA	NJ036LHXEA	
Power Supply		Φ, #, V, Hz	1,2,220-240,50	1,2,220-240,50	
Mode			HPHR	HPHR	
Performance	Capacity (Nominal)	Cooling	2.60	3.50	
			Btu/h	8,900	11,900
		Heating	2.90	3.80	
			9,900	13,000	
Power	Power Input (Nominal)	Cooling	80.00	80.00	
		Heating	80.00	80.00	
	Current Input (Nominal)	Cooling	0.40	0.40	
		Heating	0.40	0.40	
Fan	Motor	Type	Sirocco Fan	Sirocco Fan	
		Output	W	80 x 1	80 x 1
	Air Flow Rate	High / Mid / Low (UL)	CFM/L	8,607/606.60	9,808/607.80
		lit	143.33/126.67/110.00	163.33/146.67/130.00	
	External Static Pressure	Min. / Std. / Max.	mmAq	0.002/0.04/0.0	0.002/0.04/0.0
			Pa	0.0019/61/29.23	0.0019/61/29.23
Piping Connections	Liquid Pipe	Φ, mm	6.35	6.35	
		Φ, inch	1/4"	1/4"	
	Gas Pipe	Φ, mm	9.52	9.52	
		Φ, inch	3/8"	3/8"	
Drain Pipe	Φ, mm	VP25 (OD 32, ID 25)	VP25 (OD 32, ID 25)		
Field Wiring	Power Source Wire	Below 20m / Over 20m	mm ²	1.5 - 2.5	
	Transmission Cable		mm ²	0.75 - 1.50	
Refrigerant	Type			R410A	
	Control Method			EEV NOT INCLUDED	
Sound	Sound Pressure	High / Mid / Low	dBA	30.0/28.0/25.0	
			dBA	-	
	Sound Power	High / Mid / Low			-
					-
Dimensions	Net Weight		kg	26.00	
	Shipping Weight		kg	31.00	
	Net Dimensions (WxHxD)		mm	900 x 199 x 600	900 x 199 x 600
		Shipping Dimensions (WxHxD)		mm	1133 x 330 x 730
	Panel Size	Panel Model			-
Panel Net Weight			kg	-	
Shipping Weight			kg	-	
Net Dimensions (WxHxD)			mm	-	-
		Shipping Dimensions (WxHxD)		mm	-
Additional Accessories	Drain Pump	Drain Pump		MDP-E075SEE3	
		Max. Lifting Height / Displacement	mm / liter/h	-	
	Air Filter			-	

* Product Specifications in the Publication can be changed without a prior notice. Because there is always an ongoing improvement on our product.

Optional Accessories

Standard Accessories

Individual Controllers



MWR-WE10 MWR-WI00 MWR-SI00 MR-DH00 MRK-A00 MFW-10A

Drain Pump



MDP-E075SEE3

Individual Controllers

